
Instructions: Language of the Computer

Computer Architecture

2019 I 학기

한양대학교 공과대학 컴퓨터소프트웨어학부
홍석준

C Sort Example

- Illustrates use of assembly instructions for a C bubble sort function
- Swap procedure (leaf)

```
void swap(int v[], int k)
{
    int temp;
    temp = v[k];
    v[k] = v[k+1];
    v[k+1] = temp;
}
```

- v in \$a0, k in \$a1, temp in \$t0

The Procedure Swap

swap:	sll \$t1, \$a1, 2	# \$t1 = k * 4
	add \$t1, \$a0, \$t1	# \$t1 = v+(k*4)
		# (address of v[k])
	lw \$t0, 0(\$t1)	# \$t0 (temp) = v[k]
	lw \$t2, 4(\$t1)	# \$t2 = v[k+1]
	sw \$t2, 0(\$t1)	# v[k] = \$t2 (v[k+1])
	sw \$t0, 4(\$t1)	# v[k+1] = \$t0 (temp)
	jr \$ra	# return to calling routine

The Sort Procedure in C

- Non-leaf (calls swap)

```
void sort (int v[], int n)
{
    int i, j;
    for (i = 0; i < n; i += 1) {
        for (j = i - 1;
             j >= 0 && v[j] > v[j + 1];
             j -= 1) {
            swap(v, j);
        }
    }
}
```

- v in \$a0, k in \$a1, i in \$s0, j in \$s1

The Procedure Body





	move \$s2, \$a0	# save \$a0 into \$s2	Move params
	move \$s3, \$a1	# save \$a1 into \$s3	
	move \$s0, \$zero	# i = 0	
for1tst:	slt \$t0, \$s0, \$s3	# \$t0 = 0 if \$s0 ≥ \$s3 (i ≥ n)	Outer loop
	beq \$t0, \$zero, exit1	# go to exit1 if \$s0 ≥ \$s3 (i ≥ n)	
	addi \$s1, \$s0, -1	# j = i - 1	
for2tst:	slti \$t0, \$s1, 0	# \$t0 = 1 if \$s1 < 0 (j < 0)	Inner loop
	bne \$t0, \$zero, exit2	# go to exit2 if \$s1 < 0 (j < 0)	
	sll \$t1, \$s1, 2	# \$t1 = j * 4	
	add \$t2, \$s2, \$t1	# \$t2 = v + (j * 4)	
	lw \$t3, 0(\$t2)	# \$t3 = v[j]	
	lw \$t4, 4(\$t2)	# \$t4 = v[j + 1]	
	slt \$t0, \$t4, \$t3	# \$t0 = 0 if \$t4 ≥ \$t3	
	beq \$t0, \$zero, exit2	# go to exit2 if \$t4 ≥ \$t3	
	move \$a0, \$s2	# 1st param of swap is v (old \$a0)	Pass params & call
	move \$a1, \$s1	# 2nd param of swap is j	
	jal swap	# call swap procedure	
	addi \$s1, \$s1, -1	# j -= 1	
	j for2tst	# jump to test of inner loop	Inner loop
exit2:	addi \$s0, \$s0, 1	# i += 1	
	j for1tst	# jump to test of outer loop	Outer loop

The Full Procedure




sort:	addi \$sp,\$sp, -20	# make room on stack for 5 registers
	sw \$ra, 16(\$sp)	# save \$ra on stack
	sw \$s3,12(\$sp)	# save \$s3 on stack
	sw \$s2, 8(\$sp)	# save \$s2 on stack
	sw \$s1, 4(\$sp)	# save \$s1 on stack
	sw \$s0, 0(\$sp)	# save \$s0 on stack
	...	# procedure body
	...	
	exit1: lw \$s0, 0(\$sp)	# restore \$s0 from stack
	lw \$s1, 4(\$sp)	# restore \$s1 from stack
	lw \$s2, 8(\$sp)	# restore \$s2 from stack
	lw \$s3,12(\$sp)	# restore \$s3 from stack
	lw \$ra,16(\$sp)	# restore \$ra from stack
	addi \$sp,\$sp, 20	# restore stack pointer
	jr \$ra	# return to calling routine

Effect of Compiler Optimization

Compiled with gcc for Pentium 4 under Linux



Effect of Language and Algorithm



Lessons Learnt

- Instruction count and CPI are not good performance indicators in isolation
- Compiler optimizations are sensitive to the algorithm
- Java/JIT compiled code is significantly faster than JVM interpreted
 - Comparable to optimized C in some cases
- Nothing can fix a dumb algorithm!

Arrays vs. Pointers

- Array indexing involves
 - Multiplying index by element size
 - Adding to array base address
- Pointers correspond directly to memory addresses
 - Can avoid indexing complexity

Example: Clearing and Array

```
clear1(int array[], int size) {  
    int i;  
    for (i = 0; i < size; i += 1)  
        array[i] = 0;  
}
```

```
        move $t0,$zero    # i = 0  
loop1: sll $t1,$t0,2      # $t1 = i * 4  
        add $t2,$a0,$t1   # $t2 =  
                           # &array[i]  
        sw $zero, 0($t2)  # array[i] = 0  
        addi $t0,$t0,1    # i = i + 1  
        slt $t3,$t0,$a1   # $t3 =  
                           # (i < size)  
        bne $t3,$zero,loop1 # if (...)  
                           # goto loop1
```

```
clear2(int *array, int size) {  
    int *p;  
    for (p = &array[0]; p < &array[size];  
        p = p + 1)  
        *p = 0;  
}
```

```
        move $t0,$a0      # p = & array[0]  
        sll $t1,$a1,2      # $t1 = size * 4  
        add $t2,$a0,$t1   # $t2 =  
                           # &array[size]  
loop2: sw $zero,0($t0)    # Memory[p] = 0  
        addi $t0,$t0,4     # p = p + 4  
        slt $t3,$t0,$t2   # $t3 =  
                           # (p < &array[size])  
        bne $t3,$zero,loop2 # if (...)  
                           # goto loop2
```

Comparison of Array vs. Ptr

- Multiply “strength reduced” to shift
- Array version requires shift to be inside loop
 - Part of index calculation for incremented i
 - c.f. incrementing pointer
- Compiler can achieve same effect as manual use of pointers
 - Induction variable elimination
 - Better to make program clearer and safer

ARM & MIPS Similarities


- ARM: the most popular embedded core
- Similar basic set of instructions to MIPS

	ARM	MIPS
Date announced	1985	1985
Instruction size	32 bits	32 bits
Address space	32-bit flat	32-bit flat
Data alignment	Aligned	Aligned
Data addressing modes	9	3
Registers	15 × 32-bit	31 × 32-bit
Input/output	Memory mapped	Memory mapped

Compare and Branch in ARM

- Uses condition codes for result of an arithmetic/logical instruction
 - Negative, zero, carry, overflow
 - Compare instructions to set condition codes without keeping the result
- Each instruction can be conditional
 - Top 4 bits of instruction word: condition value
 - Can avoid branches over single instructions

Instruction Encoding



The Intel x86 ISA

- Evolution with backward compatibility
 - 8080 (1974): 8-bit microprocessor
 - Accumulator, plus 3 index-register pairs
 - 8086 (1978): 16-bit extension to 8080
 - Complex instruction set (CISC)
 - 8087 (1980): floating-point coprocessor
 - Adds FP instructions and register stack
 - 80286 (1982): 24-bit addresses, MMU
 - Segmented memory mapping and protection
 - 80386 (1985): 32-bit extension (now IA-32)
 - Additional addressing modes and operations
 - Paged memory mapping as well as segments

The Intel x86 ISA

- Further evolution...
 - i486 (1989): pipelined, on-chip caches and FPU
 - Compatible competitors: AMD, Cyrix, ...
 - Pentium (1993): superscalar, 64-bit datapath
 - Later versions added MMX (Multi-Media eXtension) instructions
 - The infamous FDIV bug
 - Pentium Pro (1995), Pentium II (1997)
 - New microarchitecture (see Colwell, *The Pentium Chronicles*)
 - Pentium III (1999)
 - Added SSE (Streaming SIMD Extensions) and associated registers
 - Pentium 4 (2001)
 - New microarchitecture
 - Added SSE2 instructions

The Intel x86 ISA

- And further...
 - AMD64 (2003): extended architecture to 64 bits
 - EM64T – Extended Memory 64 Technology (2004)
 - AMD64 adopted by Intel (with refinements)
 - Added SSE3 instructions
 - Intel Core (2006)
 - Added SSE4 instructions, virtual machine support
 - AMD64 (announced 2007): SSE5 instructions
 - Intel declined to follow, instead...
 - Advanced Vector Extension (announced 2008)
 - Longer SSE registers, more instructions
- If Intel didn't extend with compatibility, its competitors would!
 - Technical elegance ≠ market success

Basic x86 Registers

Name	31	0	Use
EAX			GPR 0
ECX			GPR 1
EDX			GPR 2
EBX			GPR 3
ESP			GPR 4
EBP			GPR 5
ESI			GPR 6
EDI			GPR 7
	CS		Code segment pointer
	SS		Stack segment pointer (top of stack)
	DS		Data segment pointer 0
	ES		Data segment pointer 1
	FS		Data segment pointer 2
	GS		Data segment pointer 3
EIP			Instruction pointer (PC)
EFLAGS			Condition codes

Basic x86 Addressing Modes

- Two operands per instruction

Source/dest operand	Second source operand
Register	Register
Register	Immediate
Register	Memory
Memory	Register
Memory	Immediate

- Memory addressing modes
 - Address in register
 - $\text{Address} = R_{\text{base}} + \text{displacement}$
 - $\text{Address} = R_{\text{base}} + 2^{\text{scale}} \times R_{\text{index}}$ (scale = 0, 1, 2, or 3)
 - $\text{Address} = R_{\text{base}} + 2^{\text{scale}} \times R_{\text{index}} + \text{displacement}$

x86 Instruction Encoding

a. JE EIP + displacement

4	4	8
JE	Condition	Displacement

b. CALL

8	32
CALL	Offset

c. MOV EBX, [EDI + 45]

6	1	1	8	8
MOV	d	w	r/m Postbyte	Displacement

d. PUSH ESI

5	3
PUSH	Reg

e. ADD EAX, #6765

4	3	1	32
ADD	Reg	w	Immediate

f. TEST EDX, #42

7	1	8	32
TEST	w	Postbyte	Immediate

■ Variable length encoding

- Postfix bytes specify addressing mode
- Prefix bytes modify operation
 - Operand length, repetition, locking, ...

Implementing IA-32

- Complex instruction set makes implementation difficult
 - Hardware translates instructions to simpler microoperations
 - Simple instructions: 1-1
 - Complex instructions: 1-many
 - Microengine similar to RISC
 - Market share makes this economically viable
- Comparable performance to RISC
 - Compilers avoid complex instructions

ARM v8 Instructions


- In moving to 64-bit, ARM did a complete overhaul
- ARM v8 resembles MIPS
 - Changes from v7:
 - No conditional execution field
 - Immediate field is 12-bit constant
 - Dropped load/store multiple
 - PC is no longer a GPR
 - GPR set expanded to 32
 - Addressing modes work for all word sizes
 - Divide instruction
 - Branch if equal/branch if not equal instructions

Fallacies

- Powerful instruction \Rightarrow higher performance
 - Fewer instructions required
 - But complex instructions are hard to implement
 - May slow down all instructions, including simple ones
 - Compilers are good at making fast code from simple instructions
- Use assembly code for high performance
 - But modern compilers are better at dealing with modern processors
 - More lines of code \Rightarrow more errors and less productivity

Fallacies

- Backward compatibility \Rightarrow instruction set doesn't change
 - But they do accrete more instructions



x86 instruction set

Pitfalls

- Sequential words are not at sequential addresses
 - Increment by 4, not by 1!
- Keeping a pointer to an automatic variable after procedure returns
 - e.g., passing pointer back via an argument
 - Pointer becomes invalid when stack popped

Concluding Remarks

- Design principles
 1. Simplicity favors regularity
 2. Smaller is faster
 3. Make the common case fast
 4. Good design demands good compromises
- Layers of software/hardware
 - Compiler, assembler, hardware
- MIPS: typical of RISC ISAs
 - c.f. x86

Concluding Remarks

- Measure MIPS instruction executions in benchmark programs
 - Consider making the common case fast
 - Consider compromises

Instruction class	MIPS examples	SPEC2006 Int	SPEC2006 FP
Arithmetic	add, sub, addi	16%	48%
Data transfer	lw, sw, lb, lbu, lh, lhu, sb, lui	35%	36%
Logical	and, or, nor, andi, ori, sll, srl	12%	4%
Cond. Branch	beq, bne, slt, slti, sltiu	34%	8%
Jump	j, jr, jal	2%	0%